

Prototyping MicrosemiTM Rad-Tolerant Devices

MIL/AERO



MicrosemiTM Prototyping

Aldec and Microsemi have joined together, offering a new, innovative, reprogrammable prototyping solution for Microsemi RTAX-S/SL, RTAX-DSP and RTSX-SU space-flight system designs. Unlike the traditional OTP (One Time Programmable) anti-fuse space-qualified FPGAs, the Aldec prototype adaptor uses flash-based, Microsemi ProASIC[®]3E FPGA technology, for design prototype re-programmability.

Top Features

- Supported Microsemi devices/capacities: RTAX-S/SL up to 4000S, RTAX-DSP and RTSX-SU devices
- Automated Device Netlist Converter:
 - Memory Conversion
 - Physical Design Constraint (PDC) file conversion

Microsemi ProASIC[®]3E FPGA Technology

Using ProASIC3E FPGA flash-based programming technology instead of traditional OTP anti-fuse space-qualified FPGAs (AX chips) provides significant advantages, such as a smaller device size with greater routing flexibility, more switches, lower power consumption, non-volatile re-programmability with easier technology mapping and Netlist optimizations. The Microsemi ProASIC3E FPGA family supports devices from 15,000 to 3 million ASIC gates and includes 504Kbits of true dual-port SRAM, 620 user I/Os, 1KB of flash-ROM and provides secure IP 128-bit AES encryption/decryption.

		Aldec RTAX-S/SL Prototyping Adaptors			
		RTAX250S/SL	RTAX1000S/SL	RTAX2000S/SL	RTAX4000S
CQFP PACKAGE	CQ208	•			
	CQ256			•	
	CQ352	•	•	•	•
CGA/LGA PACKAGE	CG624	•	•	•	
	CG1152			•	
	CG1272				•

		Aldec RTSX-SU Prototyping Adaptors					
		RTSX32SU	RTSX72SU	RT54SX32S	RT54SX72S	A54SX32A	A54SX72A
CQ208	•	•	•	•	•	•	
CQ256	•	•	•	•	•	•	
CG624		•		•			

		Aldec RTAX-DSP Prototyping Adaptors	
		RTAX2000D	RTAX4000D
CQ352	•		•
CG1272	•		•

Aldec Re-Programmable Prototyping Adaptors

The Aldec prototyping adaptor board maps the footprint of the Microsemi ProASIC3E FPGA device to the footprint of the Microsemi RTAX-S/SL, RTAX-DSP or RTSX-SU device (e.g. CQ208, CQ256, CQ352, CG624, CG1152 or CG1272). After soldering the adaptor to the PCB, a programming connector (JTAG) provides on-the-fly reprogramming of the device, without detaching the adaptor from the target PCB. In addition, a GUI-based EDIF Netlist Converter Application, is available for automatic pin re-mapping from anti-fuse to flash-based architecture. Aldec prototyping adaptors are available today, in a wide-variety of supported device capacities and packages.



RTAX-S/SL Prototyping Adaptors


CQ208



Description

- Microsemi ProASIC3E device
- JTAG connector
- CQ208 footprint
- Size: 37mm x 37mm

CQ256



Description

- Microsemi ProASIC3E device
- JTAG connector
- CQ256 footprint
- Size: 43.07mm x 43.07mm

CQ352



Description

- Microsemi ProASIC3E device Commercial or Industrial
- JTAG connector
- Power connector
- CQ352 footprint
- Size: 55mm x 55mm

CG624



Description

- Microsemi ProASIC3E device Commercial or Industrial
- JTAG connector
- CG624 footprint
- Size: 32.5mm x 34mm

CQ352 (RTAX-4000S)



Description


Stacked MB/DB with:

- Microsemi ProASIC3E device
- JTAG connector
- CQ352 footprint
- Size: 55mm x 55mm

EDIF Netlist Converter

The RTAX EDIF Netlist Converter, an optional application, performs automatic conversion of the RTAX-S/SL and RTSX-SU EDIF netlist to a ProASIC3E netlist, taking into consideration the differences between RTAX-S/SL or RTSX-SU anti-fuse and ProASIC3E flash-based technologies.

A pin re-mapping utility provides automatic Physical Design Constraint (PDC) file conversion, which eliminates the need for additional, time consuming manual work.



RTSX-SU Prototyping Adaptors

CQ208



Description

- Microsemi ProASIC3E device
- JTAG connector
- CQ208 footprint
- Size: 37mm x 37mm

CQ256



Description

- Microsemi ProASIC3E device
- JTAG connector
- CQ256 footprint
- Size: 43.07mm x 43.07mm

"We had a very aggressive schedule. We needed a way to quickly verify the design functionality and integrate support. The Aldec prototyping adaptor saved us two months off our development schedule and over \$72,000 off our project costs."

-Russ McGrath
Principal Engineer
Orbital Sciences Corporation



Headquarters-US
2260 Corporate Circle
Henderson, NV 89074
USA

Europe
Mercia House
51 The Green, South Bar
Banbury, OX16 9AB
United Kingdom

Israel
Even Yehuda 40500
6 Macabi St.
POB 2521
Israel

Japan
Shinjyuku Estate Bldg. 9F
1-34-15, Shinjyuku
Shinjyuku-ku, Tokyo 160-0022
Japan

China
Suite 2004, BaoAn Building
#800 DongFang Road
PuDong District
Shanghai City, 200122, P.R. China

India
#2145, 17th Main
2nd Cross, HAL 2nd Stage
Indiranagar
Bangalore, 560008, India

Taiwan
No. 37, Section 2
LiuJia 5th Road
Hsinchu County 302
Zhubei City, Taiwan

Phone: +702.990.4400
E-mail: sales@aldec.com

Phone: +44.1295. 20.1240
Email: sales-eu@aldec.com

Phone: +972.5.2257.3422
E-mail: sales-il@aldec.com

Phone: +81.3.5312.1791
Email: sales-jp@aldec.com

Phone: +86.21.6875.2030
Email: info@aldec.com.cn

Phone: +91.80.3255.1030
Email: sales-in@aldec.com

Phone: +886.3.6587712
Email: sales-tw@aldec.com



www.aldec.com